

Requested Patent: GB2336260A

Title: AGC CIRCUIT ;

Abstracted Patent: US2003086513 ;

Publication Date: 2003-05-08 ;

Inventor(s): ICHIHARA MASAKI (JP) ;

Applicant(s): ;

Application Number: US19990286074 19990405 ;

Priority Number(s): JP19980092140 19980406 ;

IPC Classification: H04L27/08 ;

Equivalents:

AU2353899, AU749189, IT1312166, ITMI990691, JP11289231, JP3329264B2 ;

#### ABSTRACT:

In an AGC circuit for correcting a variation in received level by feeding back feedback data based on the difference between the average received level and a reference value in units of slots to an AGC amplifier, when the difference between the average received level and the reference value is equal to or more than a predetermined value, the value of the feedback data is set to be larger than a normal value

# (12) UK Patent Application (19) GB (11) 2 336 260 (13) A

(43) Date of A Publication 13.10.1999

(21) Application No 9907853.7

(22) Date of Filing 06.04.1999

(30) Priority Data

(31) 10092140

(32) 06.04.1998

(33) JP

(71) Applicant(s)

NEC Corporation

(Incorporated in Japan)

7-1 Shiba 5-chome, Minato-ku, Tokyo 108-01, Japan

(72) Inventor(s)

Masaki Ichihara

(74) Agent and/or Address for Service

Mathys & Squire

100 Grays Inn Road, LONDON, WC1X 8AL,

United Kingdom

(51) INT CL<sup>6</sup>

H03G 3/20

(52) UK CL (Edition Q )

H3G GCN G12X

(56) Documents Cited

EP 0812064 A2

US 5594760 A

(58) Field of Search

UK CL (Edition Q ) H3G GCN GM GPX GPXX

INT CL<sup>6</sup> H03G 3/20 3/30


ONLINE:WPI,EPODOC,JAPIO

(54) Abstract Title

**Gain control in a CDMA receiver in which, if the deviation is greater than a set amount, the feedback is adjusted to increase the speed of convergence**


(57) In an AGC circuit for correcting a variation in received level by feeding back feedback data based on the difference between the average received level and a reference value in units of slots to an AGC amplifier, when the difference between the average received level and the reference value is equal to or more than a predetermined value, the value of the feedback data is set to be larger than a normal value. This increases the speed of convergence, overcoming the effect of a saturated D/A converter.

FIG.1  
PRIOR ART



GB 2 336 260 A

FIG.1  
PRIOR ART



2/5

FIG.2  
PRIOR ART




FIG.3  
PRIOR ART




FIG.4  
PRIOR ART





FIG.5



## AGC CIRCUIT

## BACKGROUND OF THE INVENTION

## FIELD OF THE INVENTION

5       The present invention relates to an AGC circuit for calculating the average received level per slot, obtaining the difference between the calculated level and a reference value, and feeding back the difference to an AGC amplifier, thereby correcting any variations in the  
10   received level.

## DESCRIPTION OF THE PRIOR ART

      In mobile communications, the received signal strength greatly varies (a maximum of 80 dB is expected) owing to the influences of the distance between a base  
15   station and a terminal, fading due to the movement of a terminal, shadowing due to obstacles such as buildings, and the like. To stably receive and demodulate/decode such signals, the received levels must be corrected by using an AGC (Automatic Gain Control) circuit so as to  
20   level the received baseband signals.

      This AGC circuit has been generally used in TV receivers and radios. According to a portable telephone based on the GSM or IS-95 CDMA scheme, a signal is transmitted from a base station in units of slots, and the  
25   signal is received and demodulated in units of slots on



the terminal side. In this scheme, AGC must be performed to make the gain of the AGC amplifier constant within one slot, i.e., to make the relative received signal strength constant within one slot. Such an AGC circuit cannot be realized by a conventional AGC circuit designed to perform only analog signal processing. To realize this circuit, a method including digital signal processing in Fig. 1 is required.

Fig. 1 shows a conventional AGC circuit having such an arrangement.

Fig. 1 is a block diagram showing the schematic arrangement of the AGC circuit.

Since this block diagram of Fig. 1 aims at explaining only AGC operation, other portions that are not directly associated with AGC are omitted.

In this circuit, a received signal is a QPSK-modulated wave and is demodulated into two baseband signals, i.e., an I (In-phase component) and Q (Quadrature component) signals.

The received signal is converted into an IF signal by a receiver 1. The IF signal is amplified or attenuated by an AGC amplifier 2 and demodulated into I and Q baseband signals by a quadrature demodulator 3. The I and Q signals are respectively converted into digital signals by 8-bit A/D converters 4 and 5 (not limited to 8 bits).

Assume that a CDMA scheme with a chip rate of 4.096 MHz is used as a modulation scheme, and each A/D converter samples at 16.384 MHz, which is a conversion rate four times the chip rate. Assume also that the slot length is 5 625  $\mu$  sec (i.e., 2,560 chips). In this case, therefore, each of the numbers of I and Q signal samples obtained amounts to 2560 x 4 = 10240 in a 1-slot interval.

A calculator 6 of received level calculates the average received level in the 1-slot interval from the 10 above digital I and Q signals, and outputs the calculation result as an 8-bit straight binary code.

The calculator 6 of received level calculates the average received level in the following manner (for example).

15 Since each of the I and Q signals is an 8-bit signal from a positive peak to negative peak, the absolute value of each signal is obtained first. The maximum absolute value is obtained when each signal is completely saturated to the positive and negative peaks to have a rectangular 20 waveform. This value of each of the I and Q signals is "01111111" in binary notation ("127" in decimal notation).

A received amplitude A should be calculated by:

$$A = \sqrt{I^2 + Q^2} \quad \dots(1)$$

However, since it is difficult to implement this 25 calculation by hardware, an approximate value A' given by:

$$A' = \text{Max}(|I|, |Q|) + \frac{\text{Min}(|I|, |Q|)}{2} \quad \dots (2)$$

is used. Fig. 2 shows how the amplitudes A and A' differ from each other.

The circle in Fig. 2 (sequence 3) is the result  
5 obtained by plotting a vector (I, Q) when the amplitude A is normalized with 1. A plot of the amplitude A' on each vector yields the graphic pattern of sequence 1.

As can be seen from Fig. 2, the value A' is always slightly larger than the value A. The value A' is larger  
10 than the value A by an average of about 1.087 times, i.e., about 0.723 dB. Such a difference poses no problem in the AGC circuit. When the average received level of many samples corresponding to one slot (4 x 2560 samples = 10240 samples) or more is to be obtained, we can assume  
15 that the obtained amplitude is always larger than the true amplitude by 0.723 dB.

A method of calculating the average received level in a 1-slot interval will be described next.

The average received level is obtained by dividing  
20 the sum of the values A' corresponding to one slot by the number of samples. Although the number of samples corresponding to one slot is 4 x 2560 = 10240, since it is difficult to divide by using this number,  $2^{13} = 8192$ , which is the nearest power of 2, is used.

That is, the sum is shifted by 13 bit positions to the right. In other words, the output from the calculator 6 of received level is the result obtained by adding up the approximate values  $A'$  corresponding to one slot 5 (10,240 samples) and shifting the sum by 13 bit positions to the right.

Since the maximum value of each of the I and Q signals is 127, a maximum value  $A_{max}$  obtained by the above calculation is expressed by:

$$10 \quad A_{max} = \left(127 + \frac{127}{2}\right) \times 10240 \div 8192 \approx 237 \quad \dots (3)$$

This value can be expressed by an 8-bit straight binary code.

As described above, the average received level is calculated by calculating an approximate value of the 15 average of amplitudes.

To be exact, the received level must be determined by obtaining the average of received powers. It is, however, difficult to calculate an average received power, because no suitable approximation method is available. Under the 20 circumstances, an amplitude average approximate value is unwillingly used. The difference between the received level values respectively obtained by using power averages and amplitude averages will be examined.

A received signal  $S$  from a base station has in-phase

and quadrature components written as:

$$S = I(t) \cdot \cos(2 \pi f_c t) - Q(t) \cdot \sin(2 \pi f_c t) \quad \dots (4)$$

In CDMA, since  $I(t)$  and  $Q(t)$  represent the sums of  
5 many independent speech channels, interference waves, and  
noise, the central limiting theorem holds. It therefore  
follows from this that  $I(t)$  and  $Q(t)$  each exhibit a  
Guassian distribution. If quadrature components  
respectively have independent Guassian distributions in  
10 this manner, the amplitude distribution of the synthetic  
signal exhibits a Rayleigh distribution. If amplitudes  $R$   
have a Rayleigh distribution, the probability density  
distribution is given by:

$$P(R) = \frac{R}{b_0} \cdot \exp\left(-\frac{R^2}{2 \cdot b_0}\right) \quad \dots (5)$$

15 In equation (5),  $b_0$  is a positive constant. Omitting  
a description of intermediate calculation, the power  
average is expressed by:

$$\overline{R^2} = \int_0^{\infty} R^2 \cdot \frac{R}{b_0} \cdot \exp\left(-\frac{R^2}{2 \cdot b_0}\right) \cdot dR = 2b_0 \quad \dots (6)$$

Omitting a description of intermediate calculation,  
20 the amplitude average is expressed by:

$$\overline{R} = \int_0^{\infty} R \cdot \frac{R}{b_0} \cdot \exp\left(-\frac{R^2}{2 \cdot b_0}\right) \cdot dR = \sqrt{\frac{b_0 \cdot \pi}{2}} \quad \dots (7)$$

The dB difference between the received levels  
obtained by using the power and amplitude averages is

given by:

$$d = 20 \cdot \log \left( \frac{\sqrt{R^2}}{R} \right) = \left( \frac{\sqrt{2 \cdot b_0}}{\sqrt{\frac{b_0 \cdot \pi}{2}}} \right) = 20 \cdot \log \left( \sqrt{\frac{4}{\pi}} \right) \approx 1.05 \text{ dB} \quad \dots (8)$$

That is, the received level calculated by using the power averages is equivalent to the value obtained by adding 1.05 dB to the received level calculated by using amplitude averages.

A method of determining reference level as an AGC target will be described next.

For example, the peak factor of a single code of a CDMA received signal is about 6 dB. When many users, e.g., 32 users, use this device, the peak factor increases by 30 dB to become 36 dB. It is, however, inadvisable to waste the dynamic range for a peak that rarely appears. In practice, it is probably appropriate to set the peak factor to about 10 to 12 dB. It follows from the foregoing that a value smaller than the peak value by 18 dB as a whole is appropriate as a reference value for the average received level, estimating a tracking error in AGC of about 6 dB.

Consequently, a reference value  $A_{ref}$  is given by:

$$A_{ref} = \frac{A_{max}}{10^{\frac{18}{20}}} = 29.6 \quad \dots (9)$$

Since this value is close to 32, which is the fifth

power of 2, 32 is used as a reference value for the sake of simplicity. The dB error obtained when 32 is used in place of 29.6 is about 0.68 dB. This value can almost cancel out 0.723 dB, the dB error with an approximation  
5 calculation.

Feedback amount for an AGC value is determined by comparing the average received level calculated by the calculator 6 of received level with the reference value. Assume that the gain of the AGC amplifier 2 increases as  
10 the set value in a D/A converter 13 increases. A linearizer 12 corrects nonlinearity of the control voltage/gain characteristics of the AGC amplifier 2. Since this circuit is not directly associated with the present invention, a description thereof will be omitted.

15 After the AGC value which is the result obtained by adding up feedback values through an accumulator (comprised of an adder 10 and a register 11) is corrected by the linearizer 12, the AGC amplifier 2 is controlled by the AGC control voltage obtained by converting the  
20 corrected value through the D/A converter 13.

If, therefore, the average received level is higher than the reference level, the feedback amount becomes a positive value, and vice versa. However, since the AGC value is expressed in dB, the difference between the  
25 average received level and the reference level cannot be

directly used as a feedback value.

The feedback value must be a value expressed in dB on the basis of the value obtained by dividing the average received level by the reference level. Since it is difficult to implement this calculation by means of hardware, a table 7 of feedback value, which uses an 8-bit average received level as an input address, is used in an actual circuit.

Each output from the table 7 of feedback value represents the dB difference between the average received power and the reference value. The accumulator (comprised of the adder 10 and the register 11) adds up the products of such outputs and appropriate coefficients 9. The linearizer 12 controls the AGC amplifier 2 through the D/A converter 13 by using the sum. This control is performed in units of slots.

The following problem is posed in the conventional circuit described above.

The dynamic range of the quadrature demodulator 3 is limited, and the number of bits of each of the A/D converters 4 and 5 is limited (e.g., 8 bits). If, therefore, an input signal having a received level excessively higher than the reference level is received, the A/D conversion result is saturated, as shown in Fig. 3. For this reason, as shown in Fig. 4, with regard to an



input higher than the reference level by 10-odd dB or more,  
a value (solid line) considerably smaller than the true  
value (dotted line) is used as feedback data. As a result,  
when the received signal has an excessively high level, the  
5 convergence speed of the AGC circuit decreases.

#### SUMMARY OF THE INVENTION

The present invention has been made in consideration  
of the above situation, and has as its object to provide an  
AGC circuit which exhibits a high convergence speed even  
10 when a signal having an excessively high level is abruptly  
received.

The present invention provides an AGC circuit for  
correcting a variation in the received level of a signal by  
feeding back feedback data based on a difference between an  
15 average received signal level and a reference value in  
units of slots to an AGC amplifier, wherein when the  
difference between the average received signal level and  
the reference value is not less than a predetermined value,  
a value of the feedback data is increased.

20 The feedback data may be obtained by using a table of  
feedback values.

This circuit may comprise an A/D converter for A/D-  
converting the received signal level, and the predetermined  
value may depend on the number of output bits of the A/D  
25 converter.

The predetermined value associated with the difference  
between the average received signal level and the reference

value is preferably 10 dB.

The present invention also provides a radio receiver or portable telephone comprising the AGC circuit as  
5   aforementioned.

According to the AGC circuit of the present invention, even when a signal having an excessively high level is abruptly received, the convergence speed of AGC can be increased as compared with the prior art.

10                   BRIEF DESCRIPTION OF THE DRAWINGS

Preferred features of the present invention will now be described, by way of example only, with reference to the accompanying drawings, in which:-

Fig. 1 is a block diagram schematically showing the  
15   overall arrangement of a conventional AGC circuit;

Fig. 2 is a graph showing how a received amplitude A

and its approximate value  $A'$  differ from each other;

Fig. 3 is a graph showing how an A/D converter is saturated when an input signal having a level excessively higher than a reference level is received;

5        Fig. 4 is a graph for explaining feedback data obtained when an input signal having a level excessively higher than the reference level is received; and

Fig. 5 is a graph showing the difference between the feedback data written in a table of feedback value in the prior art and that in an embodiment of the present invention.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

A preferred embodiment of the present invention will be described below with reference to the accompanying drawings.

15        The present invention relates to an AGC circuit for calculating average received levels in units of slots, obtaining the difference between each calculated level and a reference value, and feeding back the result to an AGC amplifier, thereby correcting variations in received level.

20        A circuit for obtaining feedback data by calculating the dB difference between each average received level and the reference value has been used in the prior art. A conventional equivalent scheme uses a simple dB conversion

25        table. In contrast to this, the present invention is

characterized in that when the average received level is higher than a reference level by a predetermined dB (e.g., 10 dB), a table of feedback value for obtaining feedback data larger than the value obtained by a general dB calculation is used.

The arrangement of this embodiment is nearly the same as that of the prior art in Fig. 1 except for the feedback data written in the table 7 of feedback value in Fig. 1. The following description will therefore be made with reference to Fig. 1 as well.

Fig. 5 shows the difference between the feedback data written in the table 7 of feedback value in the prior art and that in this embodiment.

Referring to Fig. 5, the abscissa represents the average received level, which falls within the range in which it can be expressed by an 8-bit straight binary code. The value "32" on the abscissa is the reference level. Referring to Fig. 5, the dashed line represents the prior art, and the solid line represents this embodiment.

Referring to Fig. 5, within the range exceeding the reference value by 0 dB or more, the calculated value of average received level becomes smaller than the value of the true level owing to the influence of saturation of the A/D converter. To correct this, according to the solid line in Fig. 5, when the calculated value of average

received level exceeds the reference value by 10 dB or more, feedback data larger than a normally calculated dB value is provided.

5 In this embodiment, when the calculated value of average received level is larger than the reference value by, e.g., 10 dB or more, the A/D converter is regarded to have saturated, and feedback data larger than the value obtained by a normal calculation is used.

10 The operation of this embodiment will be described below with reference to Fig. 1.

In the circuit shown in Fig. 1, the received signal is a QPSK-modulated wave and is demodulated into two baseband signals, i.e., an I (In-phase component) and Q (Quadrature component) signals.

15 The received signal is converted into an IF signal by a receiver 1. The IF signal is amplified or attenuated by an AGC amplifier 2 and demodulated into I and Q baseband signals by a quadrature demodulator 3. The I and Q signals are respectively converted into digital signals by  
20 8-bit A/D converters 4 and 5 (not limited to 8 bits).

Assume that CDMA with a chip rate of 4.096 MHz is used as a modulation scheme, and each of the A/D converters 4 and 5 samples at 16.384 MHz, which is a conversion rate four times the chip rate. Assume also  
25 that the slot length is 625  $\mu$ sec (i.e., 2,560 chips). In

this case, therefore, each of the numbers of I and Q signal samples obtained amounts to  $2560 \times 4 = 10240$  in a 1-slot interval.

5 A calculator 6 of received level calculates the average received level in the 1-slot interval from the above digital I and Q signals, and outputs the calculation result as an 8-bit straight binary code.

10 The calculator 6 of received level calculates the average received level in the same manner as in the prior art described above.

Feedback amount for an AGC value is determined by comparing the average received level calculated by the calculator 6 of received level with the reference value. Assume that the gain of the AGC amplifier 2 increases as  
15 the set value in a D/A converter 13 increases. A linearizer 12 corrects the nonlinearity of the control voltage/gain characteristics of the AGC amplifier 2.

After the AGC value which is the result obtained by adding up feedback values through an accumulator  
20 (comprised of an adder 10 and a register 11) is corrected by the linearizer 12, the AGC amplifier 2 is controlled by the AGC control voltage obtained by converting the corrected value through the D/A converter 13.

If, therefore, the average received level is higher  
25 than the reference level, the feedback amount becomes a

positive value, and vice versa. However, since the AGC value is expressed in dB, the difference between the average received level and the reference level cannot be directly used as a feedback value.

5       The feedback value must be a value expressed in dB on the basis of the value obtained by dividing the average received level by the reference level. Since it is difficult to implement this calculation by means of hardware, the table 7 of feedback value, which uses an  
10 8-bit average received level as an input address, is used in an actual circuit.

Each output from the table 7 of feedback value represents the dB difference between the average received power and the reference value. As described above, when  
15 the average received level is higher than the reference level by, e.g., 10 dB or more, feedback data larger than the normal dB value is output.

The accumulator (comprised of the adder 10 and the register 11) adds up the products of such outputs and  
20 appropriate coefficients 9. The linearizer 12 controls the AGC amplifier 2 through the D/A converter 13 by using the sum. This control is performed in units of slots.

Each feature disclosed in this specification (which term includes the claims) and/or shown in the drawings may be incorporated in the invention independently of other  
5 disclosed and/or illustrated features.

Statements in this specification of the "objects of the invention" relate to preferred embodiments of the invention, but not necessarily to all embodiments of the invention falling within the claims.

10 The description of the invention with reference to the drawings is by way of example only.

The text of the abstract filed herewith is repeated here as part of the specification.

In an AGC circuit for correcting a variation in  
15 received level by feeding back feedback data based on the difference between the average received level and a reference value in units of slots to an AGC amplifier, when the difference between the average received level and the reference value is equal to or more than a predetermined  
20 value, the value of the feedback data is set to be larger than a normal value.



**CLAIMS**

1. An AGC circuit for correcting a variation in the received level of a signal by feeding back feedback data  
5 based on a difference between an average received signal level and a reference value in units of slots to an AGC amplifier, wherein when the difference between the average received signal level and the reference value is not less than a predetermined value, a value of the feedback data is  
10 increased.
2. A circuit according to claim 1, wherein the feedback data is obtained by using a table of feedback values.
3. A circuit according to claim 1 or 2, wherein said  
15 circuit comprises an A/D converter for A/D-converting the received signal level, and the predetermined value depends on the number of output bits of said A/D converter.
4. A circuit according to any preceding claim, wherein the predetermined value is 10 dB.
- 20 5. A radio receiver comprising said AGC circuit according to any preceding claim.
6. A portable telephone comprising said AGC circuit according to any preceding claim.
7. An AGC circuit substantially as herein described  
25 with reference to Figures 1 and 5 of the accompanying drawings.



Application No: GB 9907853.7  
Claims searched: 1-7

Examiner: D Midgley  
Date of search: 26 July 1999

**Patents Act 1977**  
**Search Report under Section 17**

**Databases searched:**

UK Patent Office collections, including GB, EP, WO & US patent specifications, in:  
UK CI (Ed.Q): H3G GCN,GM,GPQ,GPX,GPXX  
Int CI (Ed.6): H03G 3/20,3/30  
Other: ONLINE:WPI,EPODOC,JAPIO

**Documents considered to be relevant:**

Category	Identity of document and relevant passage	Relevant to claims
A	EP 0812064 A2 (MATSUSHITA) See, for example, page 6, lines 18-23	1
A	US 5594760 (PHILIPS) whole doc.	1

X Document indicating lack of novelty or inventive step  
Y Document indicating lack of inventive step if combined with one or more other documents of same category.  
& Member of the same patent family

A Document indicating technological background and/or state of the art.  
P Document published on or after the declared priority date but before the filing date of this invention.  
E Patent document published on or after, but with priority date earlier than, the filing date of this application.